

CM-P3

Fire Alarm Control Panel

ISO9001
Approvals: CE



■ ADVANTAGES

- * Zone range is from 1 to 24 zones
- * Key-controlled function switches prevent false alarms caused by accidental touch
- * The fire alarm circuit and indicator circuit are able to detect circuit break and offer protection against short circuit

■ ORDER INFORMATION

CM-P3-1L	FACP 01 zone with battery
CM-P3-2L	FACP 02 zone with battery
CM-P3-4L	FACP 04 zone with battery
CM-P3-8L	FACP 08 zone with battery
CM-P3-12L	FACP 12 zone with battery
CM-P3-16L	FACP 16 zone with battery
CM-P3-24L	FACP 24 zone with battery

■ SPECIFICATION

MODEL NO.	CM-P3	STAND-BY BATTERY	24V DC Sealed Maintenance -Free Lead-Acid Battery	
POWER SUPPLY	240V AC 50/60Hz \pm 10%	CHARGING CURRENT	26.4V DC, under 450mA, Trickle Charge	
CHARGING VOLTAGE & CURRENT	26V DC Below 450mA Trickle Charging	DETECTORS	No limit of R.O.R. Heat or Fixed Temp. Heat detector can be installed; each circuit can connect to a maximum of 20 smoke detectors (standby current for detector: 24V DC 25 μ A below)	
EXTERNAL CIRCUIT	To-and-fro below 50 Ω		REPORT CONTACT	No-voltage Normally-Open contact point Capacity: 250V AC 7A
EOL RESISTOR	10K Ω			
NO. OF INDICATORS	1 times of panel circuits			
NO. OF BELLS	1 times of panel circuits			
CASE MATERIAL	Standard Material of 1.2mm			

■ EXTERNAL DIMENSIONS * Other circuit and dimensions can be order.

MODEL	CM-P3		
CIRCUIT NO.	1L/2L/4L/8L	12L/16L	24L
H (mm)	400	495	580
W (mm)	300	300	300
D (mm)	120	120	120

CM CHUNG MEI FIRE FIGHTING SUPPLIER CO.,LTD

CATALOG NO.CM-P3-G2-EA