

## Fire Alarm Control Panel

**ISO9001**  
**Approvals: CE**



## ■ ADVANTAGES

- \* Zone range is from 5 to 100 zones
- \* 2 stages accumulation function to prevent from false alarms
- \* With no voltage output contacts and voltage contacts
- \* The unit also can combine with our broadcast host and emergency telephone into 3-in-1 system for multipurpose

## EXTERNAL DIMENSIONS

MODEL	Wall Mounting Type					
CIRCUIT NO.	5L - 10L	15L	20L	25L - 30L	35L - 40L	45L - 50L
H (mm)	400	495	580	520	580	700
W (mm)	300	300	300	480	480	480
D (mm)	120	120	120	180	180	180

## ■ SPECIFICATION

MODEL NO.	CM-P1	CURRENT VOLTAGE	24V DC operation voltage, below 5V 32mA
POWER SUPPLY	230V AC 50/60Hz	CHARGING CURRENT	26V DC, under 450mA, Trickle Charge
STAND-BY BATTERY	24V DC	DETECTORS	No limit of R.O.R. Heat or Fixed Temp. Heat Detector can be installed; Each circuit can connect to a maximum of 20 smoke detectors (standby current for detector: 24V DC 25µA below)
EOL RESISTOR	10KΩ		
EXTERNAL CIRCUIT RESISTANCE	To-and-fro below 50 Ω		
NO. OF BELLS	1.2 times of panel circuits	NO. OF INDICATORS	1.2 times of panel circuits (LED indicator)
MAIN AUDIO	Single-tone buzzer, above 85dB	CASE MATERIAL	1.2 mm - 2.0mm Steel plate with powder coating
		REPORT CONTACT	No voltage N.O. contact Capacity 250V AC 7A × 2 sets

## ■ ORDER INFORMATION

<b>CM-P1</b>	FACP with battery	
<b>OPTION MODEL NO.</b>		<b>SPARE MODEL NO.</b>
<b>-T</b>	Optional Telephone 1 set	
<b>-A</b>	Optional no voltage contacts (5 ZONES as 1 unit)	YFP-T4(5 ZONES as 1 unit)
<b>-B</b>	Optional voltage contacts (5 ZONES as 1 unit)	YFP-T3(5 ZONES as 1 unit)
<b>-C</b>	Optional annunciator output (It need to be ordered when it's connected to Annunciator Panel : 5 ZONES as 1 unit)	YFP-T8(A): (5 ZONES as 1 unit)
		YFP-T8(B): (10 ZONES as 1 unit)
<b>-D</b>	Optional ZONE BELL (5 ZONES as 1 unit)	YFP-T3(5 ZONES as 1 unit)
		YFP-D1(5 ZONES as 1 unit)

\* Max.100L